










## Enterprise Centrex – Polycom VVX400 phoneset quick reference

Updated: Jul 2018

Features	Instructions
Dialing out	Lift the handset + (Phone no.) + [ # ] Note: Need to dial [ 9 ] before the phone no.
Intercom dialing	Lift the handset + (Extension no.) + [ # ]
Intercom dialing (using "busy lamp")	[ Busy lamp for that ext.]
Last number redial	[ Redial]
Speed dialing	To dial: Lift the handset + [ * ] + [ * ] + ([0][0] – [9][9]) + [ # ] * Customer needs to define speed dial in user portal first
Volume adjustment	Ringtone:  to decrease or increase Voice: Lift the handset +  to decrease or to increase
Holding call	To hold: (Call connected) +  To retrieve: (Call held) + 
All call forwarding	To set: [*] [0] [5] + (Phone/Extension no.) + [Dial] To cancel: [#] [0] [5] + [Dial]
Busy call forwarding	To set: [*] [2] [5] + (Phone/Extension no.) + [Dial] To cancel: [#] [2] [5] + [Dial]
No answer call forwarding	To set: [*] [3] [5] + (Phone/Extension no.) + [Dial] To cancel: [#] [3] [5] + [Dial]
Call transfer - Blind transfer	(Call connected) +  + (Extension no.) + 
Call transfer - Consultation transfer	(Call connected) +  + (Extension no.) + [ # ] + Answer and Talk  + Hang up
Conferencing call	(Call connected) + [Confrnc] + (Phone no.) + [ # ] + answer + [Confrnc]
Call park and retrieve	<u>Call park:</u> (Call connected ) + [another line key] + [ * ] [ 8 ] [ 4 ] + [ # ] + [ # ] + Hang up <u>Call retrieve:</u> Lift the handset + [ # ] [ 8 ] [ 4 ] + [ # ] + (Self extension no.) + [ # ]
Boss Sec Transfer	<u>Sec Transfer to Boss</u> 1. Sec presses "Hold" to hold the call and the boss line flashes 2. Boss presses the flashing boss line to pick call 3. Sec hang up

Listen to voicemail	[Voicemail] + (Lift handset) or (Lift handset) + [*] [9] [0]
Listen to voicemail (outside office)	From other phone: (Dial 2562 0111) + (Your phone no.) + [#] + (Your voicemail password) + [#]
Group pick-up	Lift the handset + [*] [1] [1] + [#]
Call pick-up	By feature access code, applicable to ALL extensions: Lift the handset + [*] [2] [1] + (Ringing extension no.) + [#] By "busy" lamp field, applicable to preset extensions: Lift the handset + [ Busy lamp for that ext. ]
Paging	Lift the handset + (Group Paging no.) + [#] + Announce <small>*IAD user plan or analog phone don't support Paging function</small>
Boss and secretary	Sec makes outgoing call using Boss line: Lift the handset + [ Boss line key ] + (Phone/extension no.) + [#] Sec picks up incoming call on Boss line: Lift the handset + [ Boss line key ]
Directory	[Directory]+ Choose [ BroadSoft Directory] + Select + AdvFind + Submit
Call List	[Call List]+ Choose [Type] + Choose [All Calls] / [Missed Calls] / [Received Calls]/ [Placed Calls]
IDD & chargeable call password	To lock: [*] [0] [4] + [#] + (System will prompt to enter password) + (Password) + [#] To unlock: [#] [0] [4] + [#] + (System will prompt to enter password) + (Password) + [#]
Menu	To view information menu: 

\* **Management/Secretary/Receptionist plan phone set model: Polycom VVX400**

Service hotline number: 1833 133

Enterprise Centrex help link: [http://www.pccwone.com/eng/ec\\_help.html](http://www.pccwone.com/eng/ec_help.html)

Voice mail box ad email reminder: customer is recommended to clean up voice mail box and email regularly.